

LED BA-10 Bent Tip Candelabra LED Lamp

LED

BA10 Bent Tip Candelabra LED Lamp 1.7 Watts 120V

Our Candelabra Lamp is designed as an energy-saving alternative for traditional candelabra lamps.

This bulb features a multi-directional beam pattern, making it ideal for general lighting applications. This compact lamp operates on 120 Volts and has a candelabra base.

Use in: Chandeliers, Wall Sconces, Carriage Lights, Vanity Lights, or just about anywhere, a quality candelabra base, bent tip bulb is required.

BL21C Clear, warm white, Bent Tip, BA10 Bulb

BL22F Frosted, warm white, Bent Tip, BA10 Bulb




Intensely Bright , True BA10 Bent Tip Replacement



Specifications

Part #	Watts	Bulb Style	Base	Volts	Case Pack	Product Description	Lumens	CRI
BL21C /	1.7 /	BA-10 /	E12 /	120 /	25 /	Clear, Bent tip, 2700k, warm white, 1pk box /	60 /	65
BL22F /	1.7 /	BA-10 /	E12 /	120 /	25 /	Frost, Bent tip, 2700k, warm white, 1pk box /	60 /	65



Dimensions:
Light Center Length (LCL) 1.34"
Maximum Diameter (DIA) 0.66"
Max. Overall Length(MOL) 1.71"



ISO 9001 CERTIFIED
TS 16949 CERTIFIED FACTORY

USA & CANADA
1-800-445-6611

FAX 1-800-445-6690



Phoenix, AZ
Phone: 602-268-0001
FAX: 602-268-0130

www.MillerLightingProducts.com

customerservice@millerlightingproducts.com